

PATCH MANAGEMENT ON JU-06 / JP-08

Remember to back up your patches before loading in patches.

Backup your patches

1. While holding down the BANK [2] button, turn on the power. of your JU-08/JP-08.
2. Connect your computer to the JU-06/JP-08 USB port via a USB cable.
3. Open the "JU-06" or "JP-08" drive on your computer. The backup files are located in the "BACKUP" folder of the "JU-06" or "JP-08" drive.
4. Copy that BACKUP folder to your computer.
5. After copying is completed, eject the USB drive and then disconnect the USB cable.



ROLAND JU-06
ULTIMATE PATCHES
MASTER COLLECTION



ROLAND JP-08
ULTIMATE PATCHES

Here's how to load our patches into your JU-06/JP-08:

1. Connect the JU-06/JP-08 to your computer via USB.
2. Turn on the JU-06/JP-08 while holding how the Bank 2 key on the JU-06/JP-08.
3. A "JU-06" or "JP-08" drive will show up on your computer.
4. Drag the contents of the JU-06/JP-08 Ultimate Patches BACKUP folder (not the folder itself) into the RESTORE folder on the JU-06/JP-08 drive on your computer.
5. Once the contents are done copying, press the MANUAL button on your JU-06/JP-08. Wait a few seconds (until the lights stop scrolling on your JU-06/JP-08), then restart the JU-06/JP-08.
6. The patches will now be installed.

Next page: How to create your own "mix and match" patch sets.

*Special thanks to www.breadandbuttersounds.com for use of their excellent (and free) JU-06 & JP-08 editors which we used for some of our patch creation work here.
Visit them to try them out!*



To create your own mix and match set:

Note: If you want create a mix and match set of patches, you can! But first, understand that the patch numbers on the unit do not correspond with patch numbers in the patch filename on your computer. This is important to know when creating a mix and match set. We've included a reference chart on the following page.

 JU06_PATCH33.PRM

is actually



So to make your own mix and match set, create a blank folder on your computer called BACKUP, then copy any patches (eg JU06_PATCH33.PRM etc) that you want into that folder (those patches are found in the BACKUP folder that you copied to your PC in the "Backup your patches" procedure on page 1 of this document). That BACKUP folder can then be loaded into your JU-06/JP-08 and backed up from your JU-06/JP-08 as instructed on page one of this manual.

In addition, you can renumber any of those patch filenames so they load into the JU-06/JP-08 patch slot you prefer. Just keep in mind the numbering system.

So for example, if you wanted to make Patch 1 in Bank 5 load into Patch 5 in Bank 8 instead, you rename the patch file on your pc in your BACKUP folder, like this:

rename filename

JU06_PATCH33.PRM (Patch 1 of Bank 5 - will be displayed at "15" on the synth)

to

JU06_PATCH62.PRM (Patch 6 of Bank 8 - will be displayed as "86" on the synth)

The following page contains a handy chart for reference when creating your mix and match set.



Here's a chart showing the patch number in the filename followed by the corresponding bank/patch number displayed on the JU-06 / JP-08.

eg. JU06_PATCH56.PRM / JP08_PATCH56.PRM is patch 78 on the synth display).

Should you have any difficulties feel free to contact support@ultimatepatches.com. We typically reply within 24 hours. We want you to get up and running to enjoy your patches! :)

*Patch number in Filename, followed by
Patch Number Displayed on the Synth:*

Bank 1

1 = 11
2 = 12
3 = 13
4 = 14
5 = 15
6 = 16
7 = 17
8 = 18

Bank 2

9 = 21
10 = 22
11 = 23
12 = 24
13 = 25
14 = 26
15 = 27
16 = 28

Bank 3

17 = 31
18 = 32
19 = 33
20 = 34
21 = 35
22 = 36
23 = 37
24 = 38

Bank 4

25 = 41
26 = 42
27 = 43
28 = 44
29 = 45
30 = 46
31 = 47
32 = 48

Bank 5

33 = 51
34 = 52
35 = 53
36 = 54
37 = 55
38 = 56
39 = 57
40 = 58

Bank 6

41 = 61
42 = 62
43 = 63
44 = 64
45 = 65
46 = 66
47 = 67
48 = 68

Bank 7

49 = 71
50 = 72
51 = 73
52 = 74
53 = 75
54 = 76
55 = 77
56 = 78

Bank 8

57 = 81
58 = 82
59 = 83
60 = 84
61 = 85
62 = 86
63 = 87
64 = 88

